

Electronic 4 Pin Fluorescent Lamp Technical Data

| Nominal Wattage | Lamp Base | Avg. Lamp Life (Hrs) | Initial / Mean Lumens | Color Rendering Index (CRI) | Color Temp. (K) |
|-----------------|-----------|----------------------|-----------------------|-----------------------------|------------------------------|
| 13W Quad | G24Q-1 | 12,000 | 900 / 775 | 82 | 2700 3000 3500 4100 |
| 13W TRT | GX24Q-1 | 12,000 | 900 / 774 | 82 | 2700 3000 3500 4100 |
| 18W Quad | G24Q-2 | 12,000 | 1250 / 1075 | 82 | 2700 3000 3500 4100 |
| 18W TRT | GX24Q-2 | 12,000 | 1200 / 1020 | 82 | 2700 3000 3500 4100 |
| 26W Quad | G24Q-3 | 12,000 | 1800 / 1550 | 82 | 2700 3000 3500 4100 |
| 26W TRT | GX24Q-3 | 12,000 | 1800 / 1530 | 82 | 2700 3000 3500 4100 |
| 32W TRT | GX24Q-3 | 12,000 | 2400 / 2040 | 82 | 2700 3000 3500 4100 |
| 42W TRT | GX24Q-4 | 12,000 | 3200 / 2720 | 82 | 2700 3000 3500 4100 |
| 57W TRT | GX24Q-5 | 12,000 | 4300 / 3741 | 82 | 3000 3500 4100 |

Electronic Fluorescent Ballast Technical Data

| Wattage | No. of lamps | Voltage | Input Watts | Line Current (Amps) | Min. Starting Temp. (°F / °C) |
|----------|--------------|---------|-------------|---------------------|-------------------------------|
| 13W | 1 | 120V | 16 | 0.13 | 0/-18 |
| 13W | 1 | 277V | 16 | 0.06 | 0/-18 |
| 13W | 2 | 120V | 29 | 0.25 | 0/-18 |
| 13W | 2 | 277V | 29 | 0.11 | 0/-18 |
| 13W | 3 | 120V | 45 | 0.38 | 0/-18 |
| 13W | 3 | 277V | 45 | 0.16 | 0/-18 |
| 18W Quad | 1 | 120V | 19 | 0.16 | 0/-18 |
| 18W Quad | 1 | 277V | 19 | 0.07 | 0/-18 |
| 18W Quad | 2 | 120V | 35 | 0.30 | 0/-18 |
| 18W Quad | 2 | 277V | 35 | 0.13 | 0/-18 |
| 18W Quad | 3 | 120V | 54 | 0.46 | 0/-18 |
| 18W Quad | 3 | 277V | 54 | 0.20 | 0/-18 |
| 18W TRT | 1 | 120V | 20 | 0.17 | 0/-18 |
| 18W TRT | 1 | 277V | 20 | 0.08 | 0/-18 |
| 18W TRT | 2 | 120V | 39 | 0.33 | 0/-18 |
| 18W TRT | 2 | 277V | 39 | 0.14 | 0/-18 |
| 26W Quad | 1 | 120V | 27 | 0.23 | 0/-18 |
| 26W Quad | 1 | 277V | 27 | 0.10 | 0/-18 |
| 26W Quad | 2 | 120V | 52 | 0.43 | 0/-18 |
| 26W Quad | 2 | 277V | 52 | 0.19 | 0/-18 |
| 26WQuad | 3 | 120V | 79 | 0.63 | 0/-18 |
| 26WQuad | 3 | 277V | 79 | 0.29 | 0/-18 |
| 26W TRT | 1 | 120V | 29 | 0.24 | 0/-18 |
| 26W TRT | 1 | 277V | 29 | 0.11 | 0/-18 |
| 26W TRT | 2 | 120V | 55 | 0.46 | 0/-18 |
| 26W TRT | 2 | 277V | 55 | 0.21 | 0/-18 |
| 32W | 1 | 120V | 36 | 0.31 | 0/-18 |
| 32W | 1 | 277V | 36 | 0.13 | 0/-18 |
| 32W | 2 | 120V | 68 | 0.57 | 0/-18 |
| 32W | 2 | 277V | 68 | 0.25 | 0/-18 |
| 42W | 1 | 120V | 46 | 0.38 | 0/-18 |
| 42W | 1 | 277V | 46 | 0.17 | 0/-18 |
| 42W | 2 | 120V | 93 | 0.78 | 0/-18 |
| 42W | 2 | 277V | 93 | 0.33 | 0/-18 |
| 57W | 1 | 120V | 59 | 0.80 | 0/-18 |
| 57W | 1 | 277V | 59 | 0.21 | 0/-18 |

Electronic Fluorescent Dimming Ballast Technical Data

| Wattage | No. of lamps | Voltage | Input Watts | Line Current (Amps) | Min. Starting Temp. (°F / °C) |
|---|--------------|---------|-------------|---------------------|-------------------------------|
| Advance Mark VII Dimming Ballast | | | | | |
| 13W | 1 | 120V | 18 | 0.14 | 50/10 |
| 13W | 1 | 277V | 6 | 0.07 | 50/10 |
| 13W | 2 | 120V | 32 | 0.26 | 50/10 |
| 13W | 2 | 277V | 19 | 0.12 | 50/10 |
| 18W | 1 | 120V | 20 | 0.15 | 50/10 |
| 18W | 1 | 277V | 7 | 0.08 | 50/10 |
| 18W | 2 | 120V | 41 | 0.32 | 50/10 |
| 18W | 2 | 277V | 11 | 0.15 | 50/10 |
| 26W | 1 | 120V | 28 | 0.22 | 50/10 |
| 26W | 1 | 277V | 8 | 0.10 | 50/10 |
| 26W | 2 | 120V | 49 | 0.41 | 50/10 |
| 26W | 2 | 277V | 13 | 0.18 | 50/10 |
| 32W | 1 | 120V | 34 | 0.28 | 50/10 |
| 32W | 1 | 277V | 9 | 0.13 | 50/10 |
| 32W | 2 | 120V | 75 | 0.63 | 50/10 |
| 32W | 2 | 277V | 19 | 0.21 | 50/10 |
| 42W | 1 | 120V | 46 | 0.38 | 50/10 |
| 42W | 1 | 277V | 9 | 0.17 | 50/10 |
| 42W | 2 | 120V | 98 | 0.82 | 50/10 |
| 42W | 2 | 277V | 18 | 0.36 | 50/10 |
| 57W | 1 | 120V | 65 | 0.55 | 50/10 |
| 57W | 1 | 277V | 16 | 0.24 | 50/10 |
| Advance Mark X Dimming Ballast | | | | | |
| 18W | 1 | 120V | 22 | 0.18 | 50/10 |
| 18W | 1 | 277V | 7 | 0.07 | 50/10 |
| 18W | 2 | 120V | 43 | 0.36 | 50/10 |
| 18W | 2 | 277V | 14 | 0.16 | 50/10 |
| 26W | 1 | 120V | 31 | 0.26 | 50/10 |
| 26W | 1 | 277V | 8 | 0.11 | 50/10 |
| 26W | 2 | 120V | 58 | 0.48 | 50/10 |
| 26W | 2 | 277V | 16 | 0.21 | 50/10 |
| 32W | 1 | 120V | 38 | 0.32 | 50/10 |
| 32W | 1 | 277V | 9 | 0.14 | 50/10 |
| 32W | 2 | 120V | 76 | 0.64 | 50/10 |
| 32W | 2 | 277V | 20 | 0.28 | 50/10 |
| 42W | 1 | 120V | 49 | 0.41 | 50/10 |
| 42W | 1 | 277V | 10 | 0.18 | 50/10 |
| 42W | 2 | 120V | 98 | 0.82 | 50/10 |
| 42W | 2 | 277V | 20 | 0.36 | 50/10 |
| 57W | 1 | 120V | 66 | 0.55 | 50/10 |
| 57W | 1 | 277V | 18 | 0.24 | 50/10 |

Electronic Fluorescent Dimming Ballast Technical Data

| Wattage | No. of lamps | Voltage | Input Watts | Line Current (Amps) | Min. Starting Temp. (°F / °C) |
|--|--------------|---------|-------------|---------------------|-------------------------------|
| Lutron Compact SE Dimming Ballast | | | | | |
| 18W Quad | 1 | 120V | 24 | 0.20 | 50/10 |
| 18W Quad | 1 | 277V | 22 | 0.08 | 50/10 |
| 18W Quad | 2 | 120V | 50 | 0.42 | 50/10 |
| 18W Quad | 2 | 277V | 47 | 0.17 | 50/10 |
| 18W TRT | 1 | 120V | 24 | 0.20 | 50/10 |
| 18W TRT | 1 | 277V | 22 | 0.08 | 50/10 |
| 18W TRT | 2 | 120V | 50 | 0.20 | 50/10 |
| 18W TRT | 2 | 277V | 47 | 0.17 | 50/10 |
| 26W Quad | 1 | 120V | 31 | 0.26 | 50/10 |
| 26W Quad | 1 | 277V | 33 | 0.12 | 50/10 |
| 26W Quad | 2 | 120V | 60 | 0.50 | 50/10 |
| 26W Quad | 2 | 277V | 58 | 0.21 | 50/10 |
| 26W TRT | 1 | 120V | 31 | 0.26 | 50/10 |
| 26W TRT | 1 | 277V | 33 | 0.12 | 50/10 |
| 26W TRT | 2 | 120V | 60 | 0.50 | 50/10 |
| 26W TRT | 2 | 277V | 58 | 0.21 | 50/10 |
| 32W | 1 | 120V | 37 | 0.31 | 50/10 |
| 32W | 1 | 277V | 36 | 0.13 | 50/10 |
| 32W | 2 | 120V | 71 | 0.59 | 50/10 |
| 32W | 2 | 277V | 66 | 0.24 | 50/10 |
| 42W | 1 | 120V | 47 | 0.39 | 50/10 |
| 42W | 1 | 277V | 44 | 0.16 | 50/10 |
| 42W | 2 | 120V | 80 | 0.67 | 50/10 |
| 42W | 2 | 277V | 80 | 0.29 | 50/10 |